



## **Techsense Bangladesh Ltd**

## Photoelectric Sensor Code: QMRS/0P-0F

Photoelectric sensors are ideal for the detection of differences in contrast. They detect objects depending on their surface, color and material. They are inexpensive, easy to mount and align. Diffuse sensors with background suppression ensure reliable detection regardless of the surface, color and material. Their pulse width is almost constant, even with different reflectance.

## **General Attributes**

■ Normal Sensing Range : 30...200 mm

■ Min Sensing Range : 5 mm

emission : red (630 nm)operating voltage : 10....30 Vdcload current : ≤ 100 mA

■ Outpur Voltage Drop : 2 V max. @ 100 mA

■ Supply Current : ≤ 10 μA

■ Operating temperature range : - 25°C...+ 70°C

■ temperature range : - 30°C...+ 80°C

■ output type : PNP/NPN NO/NC

■ protection degree : IP67 (EN60529)


■ housing material : PA66, PMMA

## **Application Notes**

- □ Detects Transparent Bottles

- ☑ Prevention of entry into restricted area





For further information please visit: https://goo.gl/CmpksG

We are the authorized distributor of Micro Detector in Bangladesh.





